





## Ordering Information


Model	Fixation	Pattern	Length	Power <sup>3</sup>	CRI/CCT <sup>4</sup>	Driver <sup>6</sup>	Lens	Finish <sup>7</sup>	Options
WG-BC	SW SWM	S <sup>1</sup> PC <sup>2</sup> PR <sup>2</sup> PPI <sup>2</sup> PPO <sup>2</sup> PZ <sup>2</sup>	A A x B A x B x C A x B x A x B	P0 P1 P2 P3 P4	927 930 935 940 TW <sup>5</sup>	E1 BT L1 DALI POE TQ	SSD (std) SDC	W (std) F	LEC REC LREC EM
				L M H	WD RGBW	D010 L3DAE L3DOE	EL96 DMX		



### Architectural Cove



4" minimum offset, 12" typical offset  
Can be installed in Cove or Surface Mounted.



End Caps  
BC-LEC/REC

## QUICKSHIP HOUSINGS AVAILABLE

### Luminaire

- Continuous surface wall or mullion mounted cove system that delivers an even wash of directed light to the ceiling above, and redirected light to softly illuminate the wall behind the fixture.
- Light source positioned for optimum vertical spread of illumination.
- Extruded aluminum housing, easily installed internal LED tray assembly with integral driver. Fieldreplaceable LED boards.
- 90+ CRI, 3 Step MacAdam.
- L70 (TM21 Projected 85°C) 72,000 hours. RGBW 50,000 hours. WD 36,000 hours.
- ETL and ETL-C for dry and damp locations.
- Satin clear diffuser for high efficiency and soft edge beam without striations.
- Lengths and angles factory cut to exact field dimensions. Standard and custom corners.
- Powdercoat painted.

### Fixation

- SW = Surface Wall Mount
- SWM = Surface Wall Mullion Mount

### Pattern

- S = Straight run<sup>1</sup>
- PC = Standard patterns coffer 2, 3 or 4 sided with 90° inside corners<sup>2</sup>
- PR = Standard patterns raft 2, 3 or 4 sided with 90° outside corners<sup>2</sup>
- PPI = Wall to wall / wall to ceiling, 90° inside corner<sup>2</sup>
- PPO = Wall to wall / wall to ceiling, 90° outside corner<sup>2</sup>
- PZ = Non-standard patterns and/or corners other than 90°, consult factory<sup>2</sup>

### Length

- A, B, C = specify inches to the nearest 0.25" (i.e. 72.25") For patterns specify each length (i.e. 2 sided: A x B = 72.25" x 48"; 3 sided: A x B x C; 4 sided: A x B x A x B)

### Power<sup>3</sup>

- P0 = 1.5 W/ft
- P1 = 3 W/ft
- P2 = 6 W/ft
- P3 = 10 W/ft
- P4 = 15 W/ft
- L = 2.7 W/ft WD low power (24V)
- M = 5.5 W/ft WD medium power (24V)[RGBW 7.6 W/ft]
- H = 8W/ft WD high power (24V)

### CRI / CCT (90+ CRI minimum)<sup>4</sup>

- 927 = 2700K
- 930 = 3000K
- 935 = 3500K
- 940 = 4000K
- TW = Tunable White 2200K - 4000K<sup>5</sup>
- WD = Warm Dim 1800K-3000K
- RGBW = 3000K White

### Driver (integral)<sup>6</sup>

- E1 = eldoLED 0.1% dimming, 0-10V (120-277V)
- L1 = Lutron 1% dimming, EcoSystem (120-277V)
- POE = Power over Ethernet
- BT = Wireless CAS - Casambi (Must specify BT with E1 or DALI)
- DALI = eldoLED DALI DT8 0.1% (120-277V)
- TQ = T-series for Lutron Quantum 0.1% (120-277V) [TW only]
- D010 = Osram, 10%, 0-10V dimming, 120-277V [WD only]
- L3DAE = Lutron Hi-lume 1% EcoSystem, 120-277V [WD only]
- L3DOE = Lutron Hi-lume Premier 0.1% EcoSystem, 120-277V (remote) [WD only]
- DMX = Osram + eldoLED 24V, DMX dimming [WD + RGBW Only]

### Lens

- SSD = Snap On Satin Diffuser (standard)
- SDC = Satin Clear Dust Cover

### Finish<sup>7</sup>

- W = White, 15% gloss, RAL 9010 / Tiger Drylac 009/10120 (standard)
- F = Custom finish, specify RAL

### Options

- LEC = Left end cap
- REC = Right end cap
- LREC = Left & Right end caps
- EM = Emergency LED driver (remote)

1 Standard setup assumes the cove ends at a perpendicular wall and the LED board is setback from the end to minimize light on the perpendicular wall. Contact us for options.

2 See pattern specs sheet.

3 Wattage shown does not include power supplies/drivers.

4 See photometric data sheet for delivered lumens.

5 TW offered up to P3 (10W/ft) power level.

6 See power supply page for details.

7 See Tiger Drylac color chart: [inter-lux.com/tiger](http://inter-lux.com/tiger).