4" ProTools D Downlight
Round Regressed Pinhole Cover

inter•lux

Recessed Plaster Trim

Recessed Bezel Trim

1.9" / 48mm · 2.9" / 74mm · 16.0" / 406mm · 4.0" / 100mm · 3.3" / 84mm · 6.5" / 165mm · 8.4" / 213mm

Cut Out: Ø 4.75"

Recessed Plaster Trim (RPT)

1.9" / 48mm · 2.9" / 74mm · 14.7" / 373mm · 4.0" / 100mm · 3.3" / 84mm · 5.2" / 132mm · 8.4" / 213mm

Cut Out: Ø 4.75"

Recessed Bezel Trim (RBT)

Ordering Information

Model	Fixation	Power[1,2]	CRI/CCT	Driver[4]	Cover	Lens	Beam	Finish	Options
WG-100RPTD					RRP	RSO	110		
WG-100RPTD	RPT RBT	L M H	927 930 935 940	X S D010 PEQ1 PEQ0 DFPN	RRP	RSO	110	W G	LP CP IC

Luminaire
- 4" round aperture downlight with wide distribution ambient lighting.
- 0.7" regressed, evenly illuminated, highly efficient Satin Opal Lens.
- High efficiency, high transmission lens.
- Luminaire and driver installed and maintained from below the ceiling.
- Minimum of 5.5" (127mm) ceiling void is required to install the fixture from below the ceiling (integral driver).
- Modular interchangeability throughout the entire ProTools range of products.

Fixation
- RPT = Recessed Plaster Trim
- RBT = Recessed Bezel Trim

Power[1,2]
- L = Low Power, 5.5W @ 350mA
- M = Mid Power, 8W @ 500mA
- H = High Power, 11.4W @ 700mA

CRI/CCT[3]
90+ CRI (Low/Medium/High Power)
- 927 = 2700K, (759/1074/1488 lm)
- 930 = 3000K, (771/1092/1512 lm)
- 935 = 3500K, (795/1128/1566 lm)
- 940 = 4000K, (834/1188/1638 lm)

Driver[4]
- X = Remote driver, ordered separately
- S = Standard non-dim driver, 120-277V
- D010 = EldoLED, 1%, 0-10V Driver, 120-277V
- PEQ1 = Lutron Hi-lume 1% EcoSystem, 120-277V
- PEQ0 = Lutron Hi-lume Premier 0.1% EcoSystem, 120-277V
- DFPN = Lutron Forward Phase 1% 120VAC

Cover
- RRP = Round Regressed Pinhole

Lens
- RSO = Regressed Satin Opal

Beam
- 110 = 110° Beam Angle

Finish
- W = White
- G = Gray

Options
ProTools downlights require no additional options kits for remodel & new construction
- LP = Landing Pan
- CP = Chicago Plenum Housing
- IC = IC/NC Housing

[1] Other lumen packages available, consult factory.
[2] See LED data sheet for delivered lumens.
[3] Wattage shown does not include power supplies/drivers. System wattage adds 10-20%.
[4] See power supply page for details.

whitegoods

410 381 1497   inter-lux.com   answers@inter-lux.com
Inter-lux reserves the right to make technical changes without notice.

(012020)