
### ZTA.35 Surface +Zoom

## inter•lux









# 3.2" (81.5mm) (98mm) 3.9" 1.38" (35mm) fixing CRS Ø2" (Ø50mm)

#### Luminaire

- Interior rated spot light with zoomable lens or fixed focus optics.
- Surface, stem or pole clamp mounted.
- Precision machined from 70 90% recycled aluminum.
- 95+ CRI with multiple CCTs and optics available.

#### Mounting

- SM = Surface Mounted
- ST = Stem Mounted1
- PC = Pole Clamp (clamp only, contact us for custom pole options)1
- FX = Flex Mounted (180° adjustable surface mounted, swivel arm)1

#### Power<sup>2</sup>

- = 4 = 4W (385 lm initial at 450 mA, 9.4 Vf)
- 8 = 8W (798lm initial at 250mA, 34.1Vf)

#### CCT (95+ CRI)3

- 927 = 2700K
- 930 = 3000K
- 935 = 3500K
- 940 = 4000K

#### Optic

- $Z = Zoom (21.6^{\circ} 44.9^{\circ}), 8W Only$
- N1 = Narrow 1 (13.6°), 4W Only
- N2 = Narrow 2 (17.8°), 8W Only
- M = Medium (23°), 8W Only
- F = Flood (34.6°), 8W Only
- WF = Wide Flood (54.5°), 8W Only

#### Finish (interior always matte black)

- W = Pure White, RAL9010
- BL = Matte Black
- CF = Custom finish, specify RAL

#### Accessories4

- CL = Clear Lens
- DL = Diffused Lens
- HCL = Honeycomb Louver
- SOL = Solite Lens
- SHS = Sharp Spread Lens
- SOS = Soft Spread Lens

#### Remote Driver<sup>5</sup>

- ECO30W-XXX = 0-10V EldoLED ECOdrive 30W 4W, 450mA, 1-4 fixtures 8W, 250mA, 1 fixture
- SOLO50W-XXX = 0-10V EldoLED SOLOdrive 50W 4W, 450mA, 1-8 fixtures (4 per output) 8W, 250mA, 1-2 fixtures (1 per output)
- SOLO100W-XXX = 0-10V EldoLED SOLOdrive 100W 4W, 450mA, 1-16 fixtures (4 per output) 8W, 250mA, 1-4 fixtures (1 per output)
- 1. See page 5 for details.
- 2. Wattage shown is for LED only, system wattage varies depending on driver selected.
- 3. See photometric data sheet for delivered lumens.
- 4. Holds up to two accessories. See page 6 for details.
- 5. See driver information for details.

Ordering Information								
Model	Mounting	Power <sup>2</sup>	CRI/ CCT <sup>3</sup>	Optic	Finish	Accessories <sup>4</sup>	+	Driver <sup>5</sup>
MS-ZTA35S	SM ST <sup>1</sup> PC <sup>1</sup> FX <sup>1</sup>	8	927 930 935 940	N1 N2 M F WF	W BL CF	CL DL HCL SOL SHS SOS		ECO30W-XXX SOLO50W-XXX SOLO100W-XXX
MS-ZTA35SZ (Zoom)		8		Z		303		







