


Baton_P | Pendant Luminaires | arrayLED | Driver remote | 7.3W 200mA



Ø 2.4




CRI 80

White Bk E64742	3000 K	988 lm	W	Flood	70
White Au E64741	3500 K	988 lm	T		
Black Au E64754	4000 K	1058 lm	N		

Power supply options (remote only)

ECO30W-200	SOLO50W-200	SOLO100W-200
0-10V EldoLED ECOdrive 30W for 1 fixture	0-10V EldoLED SOLOdrive 50W for 1-2 fixtures	0-10V EldoLED SOLOdrive 100W for 1-4 fixtures

Baton_P | Pendant Luminaires | arrayLED | Driver remote | 7.3W 200mA



Ø 2.4




CRI 80

White Bk E64744	3000 K	988 lm	W	Flood	70
White Au E64743	3500 K	988 lm	T		
Black Au E64755	4000 K	1058 lm	N		

Power supply options (remote only)

ECO30W-200	SOLO50W-200	SOLO100W-200
0-10V EldoLED ECOdrive 30W for 1 fixture	0-10V EldoLED SOLOdrive 50W for 1-2 fixtures	0-10V EldoLED SOLOdrive 100W for 1-4 fixtures

Baton_P | Pendant Luminaires | arrayLED | Driver remote | 3W 250mA



Ø 1.3




CRI 80

White Bk E64785	3000 K	325 lm	W	Flood	50
White Au E64786	3500 K	325 lm	T		
Black Au E64787	4000 K	351 lm	N		

Power supply options (remote only)

ECO30W-250	SOLO50W-250	SOLO100W-250
0-10V EldoLED ECOdrive 30W for 1-3 fixtures	0-10V EldoLED SOLOdrive 50W for 1-6 fixtures	0-10V EldoLED SOLOdrive 100W for 1-12 fixtures

Baton_P | Pendant Luminaires | arrayLED | Driver remote | 3W 250mA



Ø 1.3



CRI 80

White Bk E64782	3000 K	325 lm	W	Flood	50
White Au E64783	3500 K	325 lm	T		
Black Au E64784	4000 K	351 lm	N		

Power supply options (remote only)

ECO30W-250	SOLO50W-250	SOLO100W-250
0-10V EldoLED ECOdrive 30W for 1-3 fixtures	0-10V EldoLED SOLOdrive 50W for 1-6 fixtures	0-10V EldoLED SOLOdrive 100W for 1-12 fixtures